Product data sheet Characteristics

LC2D40A3FE7

TeSys D reversing contactor - 3P(3 NO) - AC-3 - <= 440 V 40 A - 115 V AC coil



Main

IVIAIII	
Commercial Status	Commercialised
Range of product	TeSys D
Product or component type	Reversing contactor
Device short name	LC2D
Contactor application	Motor control Resistive load
Utilisation category	AC-1 AC-3
Device presentation	Preassembled with reversing power busbar
Poles description	3P
Power pole contact composition	3 NO
[Ue] rated operational voltage	<= 300 V DC for power circuit <= 690 V AC 25400 Hz for power circuit
[le] rated operational current	60 A (<= 60 °C) at <= 440 V AC AC-1 for power circuit 40 A (<= 60 °C) at <= 440 V AC AC-3 for power circuit
Motor power kW	30 kW at 660690 V AC 50/60 Hz 22 kW at 500 V AC 50/60 Hz 22 kW at 415440 V AC 50/60 Hz 11 kW at 220230 V AC 50/60 Hz 18.5 kW at 380400 V AC 50/60 Hz
Motor power HP (UL / CSA)	30 hp at 460/480 V AC 50/60 Hz for 3 phases motors 3 hp at 115 V AC 50/60 Hz for 1 phase motors 10 hp at 200/208 V AC 50/60 Hz for 3 phases motors 30 hp at 575/600 V AC 50/60 Hz for 3 phases motors 10 hp at 230/240 V AC 50/60 Hz for 3 phases motors 5 hp at 230/240 V AC 50/60 Hz for 1 phase motors
Control circuit type	AC 50/60 Hz
Control circuit voltage	115 V AC 50/60 Hz
Auxiliary contact composition	1 NO + 1 NC
[Uimp] rated impulse withstand voltage	6 kV conforming to IEC 60947
Overvoltage category	III
[lth] conventional free air thermal current	60 A at <= 60 °C for power circuit 10 A at <= 60 °C for signalling circuit
Irms rated making ca- pacity	800 A at 440 V for power circuit conforming to IEC 60947 250 A DC for signalling circuit conforming to IEC 60947-5-1 140 A AC for signalling circuit conforming to IEC 60947-5-1
Rated breaking capacity	800 A at 440 V for power circuit conforming to IEC 60947
[Icw] rated short-time withstand current	720 A <= 40 °C 1 s power circuit 320 A <= 40 °C 10 s power circuit 165 A <= 40 °C 1 min power circuit 72 A <= 40 °C 10 min power circuit 140 A 100 ms signalling circuit 120 A 500 ms signalling circuit 100 A 1 s signalling circuit

cable end Power circuit: EverLink BTR screw connectors 1		
[UI] rated insulation voltage 600 V for signalling circuit certifications UL 600 V for signalling circuit certifications CSA 690 V for signalling circuit conforming to IEC 60947-1 600 V for power circuit certifications UL 600 V for power circuit certifications CSA 690 V for power circuit certifications 8	Associated fuse rating	circuit 80 A gG at <= 690 V coordination type 1 for power circuit 10 A gG for signalling circuit conforming to IEC
voltage	Average impedance	1.50 mOhm at 50 Hz - Ith 60 A for power circuit
1.5 Moycles 40 A AC-3 at Ue <= 440 V		600 V for signalling circuit certifications CSA 690 V for signalling circuit conforming to IEC 60947-1 600 V for power circuit certifications UL 600 V for power circuit certifications CSA
pole 2.4 W AC-3 Safety cover With Interlocking type Mechanical Mounting support Plate Rail Standards EN 60947-4-1	Electrical durability	•
Interlocking type Mechanical Mounting support Plate Rail Standards EN 60947-4-1 EN 60947-5-1 IEC 60947-5-1 IEC 60947-5-1 UL 508 CSA C22.2 No 14 Product certifications CCC CSA GOST UL Connections - terminals Control circuit: spring terminals 2 cable(s) 0.752.5 mm² - cable stiffness: flexible - without cable end Control circuit: spring terminals 1 cable(s) 0.752.5 mm² - cable stiffness: flexible - without cable end Power circuit: EverLink BTR screw connectors 2 cable(s) 125 mm² - cable stiffness: solid - without cable end Power circuit: EverLink BTR screw connectors 1 cable(s) 135 mm² - cable stiffness: solid - without cable end Power circuit: EverLink BTR screw connectors 2 cable(s) 125 mm² - cable stiffness: flexible - with cable end Power circuit: EverLink BTR screw connectors 1 cable(s) 135 mm² - cable stiffness: flexible - with cable end Power circuit: EverLink BTR screw connectors 1 cable(s) 135 mm² - cable stiffness: flexible - with cable end Power circuit: EverLink BTR screw connectors 2 cable(s) 135 mm² - cable stiffness: flexible - with cable end Power circuit: EverLink BTR screw connectors 1 cable(s) 135 mm² - cable stiffness: flexible - without cable end Power circuit: EverLink BTR screw connectors 1 cable(s) 135 mm² - cable stiffness: flexible - without cable end Power circuit: S N.m - on EverLink BTR screw connectors - cable 2535 mm² hexagonal 4 mm Power circuit: 5 N.m - on EverLink BTR screw connectors - cable c 25 mm² hexagonal 4 mm Power circuit: 5 N.m - on EverLink BTR screw connectors - cable c 25 mm² hexagonal 4 mm Power circuit: 5 N.m - on EverLink BTR screw connectors - cable c 25 mm² hexagonal 4 mm Power circuit: 5 N.m - on EverLink BTR screw connectors - cable c 25 mm² hexagonal 4 mm Power circuit: 5 N.m - on EverLink BTR screw connectors - cable c 25 mm² hexagonal 4 mm Power circuit: 5 N.m - on EverLink BTR screw connectors - cable c 25 mm² hexagonal 4 mm Power circuit: 5 N.m - on EverLink BTR screw connectors - cable c 25 mm² hexagonal 4 mm Power		
Mounting support Plate Rail Standards EN 60947-4-1 EN 60947-5-1 IEC 60947-5-1 IEC 60947-5-1 IEC 60947-5-1 UL 508 CSA C22.2 No 14 Product certifications CCC CSA GOST UL Connections - terminals Control circuit: spring terminals 2 cable(s) 0.752.5 mm² - cable stiffness: flexible - without cable end Control circuit: spring terminals 1 cable(s) 0.752.5 mm² - cable stiffness: flexible - without cable end Power circuit: EverLink BTR screw connectors 2 cable(s) 125 mm² - cable stiffness: solid - without cable end Power circuit: EverLink BTR screw connectors 1 cable(s) 135 mm² - cable stiffness: solid - without cable end Power circuit: EverLink BTR screw connectors 2 cable(s) 125 mm² - cable stiffness: flexible - without cable end Power circuit: EverLink BTR screw connectors 2 cable(s) 135 mm² - cable stiffness: flexible - with cable end Power circuit: EverLink BTR screw connectors 1 cable(s) 135 mm² - cable stiffness: flexible - with cable end Power circuit: EverLink BTR screw connectors 2 cable(s) 135 mm² - cable stiffness: flexible - without cable end Power circuit: EverLink BTR screw connectors 2 cable(s) 135 mm² - cable stiffness: flexible - without cable end Power circuit: EverLink BTR screw connectors 1 cable(s) 135 mm² - cable stiffness: flexible - without cable end Power circuit: EverLink BTR screw connectors 1 cable(s) 135 mm² - cable stiffness: flexible - without cable end Power circuit: EverLink BTR screw connectors - cable 2535 mm² hexagonal 4 mm Power circuit: 5 N.m - on EverLink BTR screw connectors - cable 2535 mm² hexagonal 4 mm Power circuit: 5 N.m - on EverLink BTR screw connectors - cable 2535 mm² hexagonal 4 mm Power circuit: 5 N.m - on EverLink BTR screw connectors - cable 2535 mm² hexagonal 4 mm Power circuit: 5 N.m - on EverLink BTR screw connectors - cable 2535 mm² hexagonal 4 mm Power circuit: 5 N.m - on EverLink BTR screw connectors - cable 2535 mm² hexagonal 4 mm Power circuit: 5 N.m - on EverLink 5 RTR screw connectors - cable 2535	Safety cover	With
Rail Standards EN 60947-4-1 EN 60947-5-1 IEC 60947-5-1 IEC 60947-5-1 UL 508 CSA C22.2 No 14 Product certifications CCC CSA GOST UL Connections - terminals Control circuit: spring terminals 2 cable(s) 0.752.5 mm² - cable stiffness: flexible - without cable end Control circuit: spring terminals 1 cable(s) 0.752.5 mm² - cable stiffness: flexible - without cable end Power circuit: EverLink BTR screw connectors 2 cable(s) 125 mm² - cable stiffness: solid - without cable end Power circuit: EverLink BTR screw connectors 1 cable(s) 135 mm² - cable stiffness: flexible - with cable end Power circuit: EverLink BTR screw connectors 2 cable(s) 135 mm² - cable stiffness: flexible - with cable end Power circuit: EverLink BTR screw connectors 1 cable(s) 135 mm² - cable stiffness: flexible - with cable end Power circuit: EverLink BTR screw connectors 1 cable(s) 135 mm² - cable stiffness: flexible - with cable end Power circuit: EverLink BTR screw connectors 2 cable(s) 135 mm² - cable stiffness: flexible - with cable end Power circuit: EverLink BTR screw connectors 1 cable(s) 135 mm² - cable stiffness: flexible - without cable end Power circuit: EverLink BTR screw connectors 1 cable(s) 135 mm² - cable stiffness: flexible - without cable end Power circuit: EverLink BTR screw connectors - cable end Power circuit: EverLink BTR screw connectors - cable end Power circuit: EverLink BTR screw connectors - cable end Power circuit: EverLink BTR screw connectors - cable end Power circuit: EverLink BTR screw connectors - cable end Power circuit: EverLink BTR screw connectors - cable end Power circuit: EverLink BTR screw connectors - cable end Power circuit: EverLink BTR screw connectors - cable end Power circuit: EverLink BTR screw connectors - cable end Power circuit: EverLink BTR screw connectors - cable end Power circuit: EverLink BTR screw connectors - cable end Power circuit: EverLink BTR screw connectors - cable end Power circuit: EverLink BTR screw connectors - cable end Power circuit: EverLink BT	Interlocking type	Mechanical
EN 60947-5-1 IEC 60947-5-1 IEC 60947-5-1 UL 508 CSA C22.2 No 14 Product certifications CCC CSA GOST UL Connections - terminals Control circuit: spring terminals 2 cable(s) 0.752.5 mm² - cable stiffness: flexible - without cable end Control circuit: spring terminals 1 cable(s) 0.752.5 mm² - cable stiffness: flexible - without cable end Power circuit: EverLink BTR screw connectors 2 cable(s) 125 mm² - cable stiffness: solid - without cable end Power circuit: EverLink BTR screw connectors 1 cable(s) 135 mm² - cable stiffness: solid - without cable end Power circuit: EverLink BTR screw connectors 2 cable(s) 125 mm² - cable stiffness: flexible - with cable end Power circuit: EverLink BTR screw connectors 2 cable(s) 125 mm² - cable stiffness: flexible - with cable end Power circuit: EverLink BTR screw connectors 1 cable(s) 135 mm² - cable stiffness: flexible - with cable end Power circuit: EverLink BTR screw connectors 2 cable(s) 135 mm² - cable stiffness: flexible - without cable end Power circuit: EverLink BTR screw connectors 1 cable(s) 135 mm² - cable stiffness: flexible - without cable end Power circuit: EverLink BTR screw connectors 1 cable(s) 135 mm² - cable stiffness: flexible - without cable end Power circuit: EverLink BTR screw connectors 1 cable(s) 135 mm² - cable stiffness: flexible - without cable end Power circuit: EverLink BTR screw connectors - cable end Power circuit: EverLink BTR screw connectors - cable end Power circuit: 5 N.m - on EverLink BTR screw connectors - cable end Power circuit: 5 N.m - on EverLink BTR screw connectors - cable end Power circuit: 5 N.m - on EverLink BTR screw connectors - cable end Power circuit: 5 N.m - on EverLink BTR screw connectors - cable end Power circuit: 5 N.m - on EverLink BTR screw connectors - cable end Power circuit: 5 N.m - on EverLink BTR screw connectors - cable end Power circuit: 5 N.m - on EverLink BTR screw connectors - cable end Power circuit: 5 N.m - on EverLink BTR screw connectors - cable end	Mounting support	
CSA GOST UL Connections - terminals Control circuit: spring terminals 2 cable(s) 0.752.5 mm² - cable stiffness: flexible - without cable end Control circuit: spring terminals 1 cable(s) 0.752.5 mm² - cable stiffness: flexible - without cable end Power circuit: EverLink BTR screw connectors 2 cable(s) 125 mm² - cable stiffness: solid - without cable end Power circuit: EverLink BTR screw connectors 1 cable(s) 135 mm² - cable stiffness: solid - without cable end Power circuit: EverLink BTR screw connectors 2 cable(s) 125 mm² - cable stiffness: flexible - with cable end Power circuit: EverLink BTR screw connectors 1 cable(s) 135 mm² - cable stiffness: flexible - with cable end Power circuit: EverLink BTR screw connectors 2 cable(s) 125 mm² - cable stiffness: flexible - without cable end Power circuit: EverLink BTR screw connectors 1 cable(s) 135 mm² - cable stiffness: flexible - without cable end Power circuit: EverLink BTR screw connectors 1 cable(s) 135 mm² - cable stiffness: flexible - without cable end Power circuit: 5 N.m - on EverLink BTR screw con- nectors - cable 2535 mm² hexagonal 4 mm Power circuit: 5 N.m - on EverLink BTR screw con- nectors - cable 25 mm² hexagonal 4 mm Operating time 1226 ms closing 419 ms opening Safety reliability level B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO 13849-1 B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1	Standards	EN 60947-5-1 IEC 60947-4-1 IEC 60947-5-1 UL 508
mm² - cable stiffness: flexible - without cable end Control circuit: spring terminals 1 cable(s) 0.752.5 mm² - cable stiffness: flexible - without cable end Power circuit: EverLink BTR screw connectors 2 cable(s) 125 mm² - cable stiffness: solid - without cable end Power circuit: EverLink BTR screw connectors 1 cable(s) 135 mm² - cable stiffness: solid - without cable end Power circuit: EverLink BTR screw connectors 2 cable(s) 125 mm² - cable stiffness: flexible - with cable end Power circuit: EverLink BTR screw connectors 1 cable(s) 135 mm² - cable stiffness: flexible - with cable end Power circuit: EverLink BTR screw connectors 2 cable(s) 135 mm² - cable stiffness: flexible - without cable end Power circuit: EverLink BTR screw connectors 2 cable(s) 135 mm² - cable stiffness: flexible - without cable end Power circuit: EverLink BTR screw connectors 1 cable(s) 135 mm² - cable stiffness: flexible - without cable end Power circuit: 5 N.m - on EverLink BTR screw connectors - cable = cable 2535 mm² hexagonal 4 mm Power circuit: 5 N.m - on EverLink BTR screw connectors - cable <= 25 mm² hexagonal 4 mm Power circuit: 5 N.m - on EverLink BTR screw connectors - cable <= 25 mm² hexagonal 4 mm Operating time 1226 ms closing 419 ms opening Safety reliability level B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO 13849-1 B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1	Product certifications	CSA GOST
nectors - cable 2535 mm² hexagonal 4 mm Power circuit: 5 N.m - on EverLink BTR screw connectors - cable <= 25 mm² hexagonal 4 mm Operating time 1226 ms closing 419 ms opening Safety reliability level B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO 13849-1 B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 Mechanical durability 6 Mcycles		mm² - cable stiffness: flexible - without cable end Control circuit: spring terminals 1 cable(s) 0.752.5 mm² - cable stiffness: flexible - without cable end Power circuit: EverLink BTR screw connectors 2 cable(s) 125 mm² - cable stiffness: solid - without cable end Power circuit: EverLink BTR screw connectors 1 cable(s) 135 mm² - cable stiffness: solid - without cable end Power circuit: EverLink BTR screw connectors 2 cable(s) 125 mm² - cable stiffness: flexible - with cable end Power circuit: EverLink BTR screw connectors 1 cable(s) 135 mm² - cable stiffness: flexible - with cable end Power circuit: EverLink BTR screw connectors 2 cable(s) 125 mm² - cable stiffness: flexible - with cable end Power circuit: EverLink BTR screw connectors 2 cable(s) 125 mm² - cable stiffness: flexible - without cable end Power circuit: EverLink BTR screw connectors 1 cable(s) 135 mm² - cable stiffness: flexible - without cable end
419 ms opening Safety reliability level B10d = 20000000 cycles contactor with mechanical load conforming to EN/ISO 13849-1 B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 Mechanical durability 6 Mcycles	Tightening torque	nectors - cable 2535 mm² hexagonal 4 mm Power circuit: 5 N.m - on EverLink BTR screw con-
load conforming to EN/ISO 13849-1 B10d = 1369863 cycles contactor with nominal load conforming to EN/ISO 13849-1 Mechanical durability 6 Mcycles	Operating time	· ·
	Safety reliability level	load conforming to EN/ISO 13849-1 B10d = 1369863 cycles contactor with nominal load
Operating rate 3600 cyc/h at <= 60 °C	Mechanical durability	6 Mcycles
	Operating rate	3600 cyc/h at <= 60 °C



Complementary

Coil technology	Without built-in suppressor module
Control circuit voltage limits	0.851.1 Uc at 60 °C operational 60 Hz 0.81.1 Uc at 60 °C operational 50 Hz 0.30.6 Uc at 60 °C drop-out 50/60 Hz
Inrush power in VA	160 VA at 20 °C (cos φ 0.75) 50 Hz 140 VA at 20 °C (cos φ 0.75) 60 Hz
Hold-in power consumption in VA	15 VA at 20 °C (cos φ 0.3) 50 Hz 13 VA at 20 °C (cos φ 0.3) 60 Hz
Heat dissipation	45 W at 50/60 Hz
Auxiliary contacts type	Type mirror contact (1 NC) conforming to IEC 60947-4-1 Type mechanically linked (1 NO + 1 NC) conforming to IEC 60947-5-1
Signalling circuit frequency	25400 Hz
Minimum switching current	5 mA for signalling circuit
Minimum switching voltage	17 V for signalling circuit
Non-overlap time	1.5 ms on energisation (between NC and NO contact)1.5 ms on de-energisation (between NC and NO contact)
Insulation resistance	> 10 MOhm for signalling circuit

Environment

IP degree of protection	IP2x front face conforming to IEC 60529
Protective treatment	TH conforming to IEC 60068-2-30
Pollution degree	3
Ambient air temperature for operation	-560 °C
Ambient air temperature for storage	-6080 °C
Permissible ambient air temperature around the device	-4070 °C at Uc
Operating altitude	3000 m without derating in temperature
Fire resistance	850 °C conforming to IEC 60695-2-1
Flame retardance	V1 conforming to UL 94
Mechanical robustness	Shocks contactor closed 15 Gn for 11 ms Shocks contactor open 10 Gn for 11 ms Vibrations contactor closed 4 Gn, 5300 Hz Vibrations contactor open 2 Gn, 5300 Hz
Height	122 mm
Width	119 mm
Depth	120 mm
Product weight	1.87 kg

Contractual warranty

Period	18 months